


Setting up and controlling your new Vossloh-Schwabe LightBox

Ref. No.: 186513

Windows Startup



The LightBox will automatically sign in without any password and will automatically connect to the D-Link WiFi.

User name: Vossloh-Schwabe
Password:

ATTENTION: No password needed!

On-site Installation for stand-alone operation



Step 1:

This system is now preconfigured as a stand-alone DHCP-Server. The port Ethernet port must be directly connected to the Light Controller IP by ethernet (RJ45 cable). Please carefully read the quick-start-guide for Light Controller IP for further information.

Configuration & Control option 1:

- Connect a HDMI/VGA display plus keyboard & mouse and go to website <http://127.0.0.1>

Configuration & Control option 2 (requires successful set-up of step 1 above):

- Connect your mobile WiFi device (iOS/Android) according to the manual enclosed

Configuration & Control option 3:

- Connect a laptop (setting: DHCP auto, no proxy) to the Light Controller via ethernet
- Go to website <http://192.168.137.1>

Configuration & Control option 4:

- Use an accesspoint, ensure that it has no DHCP server enabled and assign it the static IP-address 192.168.137.2
- Connect to a mobile device (with the WiFi-Key of your accesspoint)
- Go to website <http://192.168.137.1>

Step 2:

Go to VS Lighting Browser

User: admin

Password: admin



Please change password after first setup. Follow the quick-start-guide instructions for Light Controller IP.

Note down your login details here:

User name

Password

